# BEU8642-EVAL

## Description

The CAES 8642-EVAL is a Lithium-Ion battery cell balancer. It provides voltage balancing among eight series stacked cells within a multi-cell battery to actively drive the voltage of each cell towards the average voltage of all cells using a patented charge-sharing technology.

### Features

- Cell Balancing of eight series stacked Lithium-Ion cells
- Transfer Ratio: 1 ohm nominal
- Cell Balancing to within ±10 mV
- Temperature Monitoring
- Cell Voltage Monitoring with high cell and low cell detection
- Built In Test (BIT) Discrete Output
- Suitable for a wide range of cell capacities, from less than 1 A-h to greater than 200 A-h
- RS-232 Output for data logging
- LCD Display for cell voltages, temperatures and status

### Benefits

When Lithium-Ion battery cells are charged and discharged, small differences in the internal electrical characteristics of each cell may lead to cell voltage differences. At beginning of life, battery manufacturers take great care to match the cell characteristics very precisely. After many charge cycles, the characteristics diverge, causing cell voltage imbalances. Since the battery can only be charged until the highest cell reaches the maximum allowed voltage, the remaining cells are never fully charged. Similarly, as the battery is discharged, the battery must be disconnected when the lowest cell reaches the minimum allowed voltage, thereby preventing the charge in the remaining cells from being used.

By keeping the cells balanced the useful capacity and life of the battery are maximized.

The 8642-EVAL provides continuous balancing for maximum protection against non-balance of Lithium-Ion cells.





**RELEASED 1/29/09** 

Balancing for 8-Cell Battery Cell Voltage Monitoring Temperature Monitoring

# BEU8642-EVAL

## Safety

The 8642-EVAL incorporates fuses to protect the battery in the event of a balancing circuit failure, as well as fuses to protect the 8642-EVAL if a battery cell fails.

The maximum balancing current supplied by the 8642-EVAL is 1A. All cells must be balanced to be within 1V before connecting the 8642-EVAL to the battery.

High cell detection can be used to prevent overcharging. Low cell detection can be used to prevent deep discharge.



Balancer Block Diagram



# BEU8642-EVAL

## **Organization and Application**

The CAES BEU8642-EVAL contains eight cell balancing circuits. Each cell balancing circuit is connected in parallel with one of the stacked cells of a multi-cell Lithium-Ion battery. In operation, energy is shared among the cells of the battery by way of the balancing circuits.

The point in the circuit of energy exchange is called the Share Bus, which represents the average voltage of all the cells. Those cells having higher voltages deliver energy to the Share Bus while those cells with lower voltages receive energy from the Share Bus.

The nominal impedance between each cell and the Share Bus, also known as the transfer ratio, is 1 ohm. This ratio determines the amount of balancing current and is based on the voltage difference between each cell and the Share Bus. For example a cell that is 200mV higher than the Share Bus will deliver 200mA to the Share Bus, whereas a cell that is 100mV less than the Share Bus will receive 100mA charging current from the Share Bus.

## **Technical Specifications**

#### **A.Cell Balancing**

•	
Number of Cells:	8
Transfer Ratio:	1 ohm nominal (0.8 ohms to 1.39 ohms)
Cell Voltage Range:	2.0 volts to 4.5 volts
Cell Balancing Current:	1.0 amperes maximum

### **B.Cell Voltage Monitoring**

**Discrete Cell Voltage Monitor Outputs:** There are two discrete Cell Voltage Monitor Outputs: High Cell (HC) and Low Cell (LC). Each output circuit is an NPN transistor, rated at 100 mA and 40 V<sub>DC</sub>, suitable for driving an LED. The transistor turns on when the measured cell voltage of any cell is outside the set limits. For example, if the HC limit is set at 4.200 volts, the transistor turns on if any measured cell voltage is greater than 4.200 volts. If the LC limit is set at 3.200 volts, the transistor turns on if any measured cell voltage is lower than 3.200 volts.

**Hysteresis:** Each detection circuit has a hysteresis of 30 mV. For example, the HC limit turns on when any cell voltage exceeds 4.200 volts. It remains on until the voltage drops below 4.170 volts.

**Voltage Measurement Accuracy:** Cell voltage monitoring accuracy is  $\pm$  10 mV, over the range of 2.000 volts to 4.500 volts.

### **C.** Temperature Monitoring

Number of sensors: 4 (Typically located in battery)

Sensor Type: NTC Thermistor Type: Keystone RL0503-55.36K-122-MS2 100KΩ

**Thresholds:** Each sensor has an Upper Threshold (UT) and a Lower Threshold (LT). For example, the UT may be set at 70°C and the LT may be set at 0°C.

**Processing:** Threshold voltages for Sensors 1 and 2 are set by the Control Logic. Thresholds for Sensors 3 and 4 are set by separate analog circuits. The Sensor 1, 2 circuits and the Sensor 3, 4 circuits are independent, so that a failure in either section does not affect the performance of the other section.



# BEU8642-EVAL

**Setting of Analog Thresholds:** The analog thresholds (Sensors 3 and 4) are set by potentiometers, with resolution of 1°C.

**Temperature Accuracy:** Measurement accuracy of the 8642-EVAL unit (independent of the accuracy of the thermistors) is less than  $\pm$  3°C, over the range of -10°C to +80°C.

**Discrete Temperature Monitor Outputs:** There are four Temperature Sensor Monitor outputs (one for each sensor). Each output circuit is an NPN transistor, rated at 100 mA and 40  $V_{DC}$ , suitable for driving an LED. The transistor turns on when the measured temperature is outside the set limits. For example, if the limits are set at 0°C and 70°C, the transistor is off when the temperature is between 0°C and 70°C, and turns on when the temperature is less than 0°C or greater than 70°C, within the specified accuracy limits.

### D.Built In Test (BIT) Discrete Output

**BIT Functions:** The Control Logic autonomously performs a series of internal tests to verify that the circuits are operating correctly. These tests include measuring:

2V reference 4V reference Power Supply Monitor PLL frequency PLL closed loop Open/shorted temperature sensors (all 4)

BIT Output: The "All OK" LED is lit and the discrete output is high when no errors are detected by BIT.

### **E.** Power Supply

**Input Voltage:** The balancing unit meets all functional requirements for input voltages from 16.0  $V_{DC}$  to 34.0  $V_{DC}$ .

**Brownout Protection:** No damage (to either the 8642-EVAL card or the battery) can occur for any input voltage between 0  $V_{DC}$  and 34.0  $V_{DC}$ .

### F. On/Off Control Circuit

**Latching Relay:** A latching relay is included on the card. When this relay is latched (turned on), the DC-DC converter output voltages are on, and the balancing card operates. When the latching relay is reset (turned off), the balancing card is inactive. The latching relay is magnetically latched, and maintains its state without power.

**On Command:** The On command must be a pulse with amplitude of 16.0 volts to 34.0 volts and pulse width of 10.0 milliseconds or greater.

**Off Command:** The Off command must be a pulse with amplitude of 16.0 volts to 34.0 volts and pulse width of 10.0 milliseconds or greater.



## BEU8642-EVAL

#### **G.Settings in Nonvolatile Memory**

**Nonvolatile Memory:** The Control Logic contains a nonvolatile memory which holds settings for certain functions. These settings can be customized at the factory. These settings include the following:

- 1) Hi Cell limit (1.25mV/bit)
- 2) Lo Cell limit (1.25 mV/bit)
- 3) Hi Temp 1 limit (2's complement degrees C)
- 4) Lo Temp 1 limit (2's complement degrees C)
- 5) Hi Temp 2 limit (2's complement degrees C)
- 6) Lo Temp 2 limit (2's complement degrees C)
- 7) Hi/Lo Cell hysteresis (1.25mV/bit)
- 8) In Balance limit (1.25mV/bit)
- 9) Out of Balance limit (1.25mV/bit)
- 10) Balancing duty cycle [1/(n+1)]

#### **H.Panel LED Indicators.**

**LED Indicators:** There are 8 LEDs on the top panel of the 8642-EVAL for quick status of the following parameters:

- 1) BALANCE ACTIVE: This LED is on when the balancer clock is functioning properly.
- 2) ALL OK: This LED is on when there are no errors detected by the BIT circuit, which monitors the following parameters:
  - a) 2V internal reference
  - b) 4V internal reference
  - c) Power Supply Monitor
  - d) PLL frequency
  - e) PLL closed loop
  - f) Open or shorted temperature sensors (all 4)
- 3) TEMPERATURE ERROR 4: This LED is on when the temperature sampled by sensor 4 is not within the range set by sensor 4's upper and lower thresholds.
- 4) TEMPERATURE ERROR 3: This LED is on when the temperature sampled by sensor 3 is not within the range set by sensor 3's upper and lower thresholds.
- 5) TEMPERATURE ERROR 2: This LED is on when the temperature sampled by sensor 2 is not within the range set by sensor 2's upper and lower thresholds.
- 6) TEMPERATURE ERROR 1: This LED is on when the temperature sampled by sensor 1 is not within the range set by sensor 1's upper and lower thresholds.
- 7) LOW CELL: This LED will be on when the voltage on any of the 8 cells falls below 3.20 volts.
- 8) HIGH CELL: This LED will be on when the voltage on any of the 8 cells exceeds 4.20 volts



RELEASED 1/29/09

Balancing for 8-Cell Battery Cell Voltage Monitoring Temperature Monitoring

## BEU8642-EVAL

#### I. Serial Output

RS232 Serial Digital Output: Continuously outputs the following values:

2V reference voltage 4V reference voltage Cell 1 voltage Cell 2 voltage Cell 3 voltage Cell 4 voltage Cell 5 voltage Cell 6 voltage Cell 7 voltage Cell 8 voltage Thermistor 1 temperature Thermistor 2 temperature Thermistor 3 temperature Thermistor 4 temperature Power supply monitor voltage

These values are outputted in a comma-separated value ASCII format at 115.2K BAUD, 1 stop bit and no parity. Each measurement is updated approximately every 30 seconds.

### J. LCD Display

Continuously outputs the following values:

Built-in test status 2V reference voltage 4V reference voltage Cell 1 voltage Cell 2 voltage Cell 3 voltage Cell 4 voltage Cell 5 voltage Cell 6 voltage Cell 7 voltage Cell 8 voltage Thermistor 1 temperature Thermistor 2 temperature Thermistor 3 temperature Thermistor 4 temperature Power supply monitor voltage

### **K.**Preconditioning

Function: A voltage applied between this pin and CELL\_RTN, to pre-charge the input capacitors to match each balancer cell's voltage with its mating battery cell's voltage, which prevents large in-rush currents when the battery is connected to the balancer.



## BEU8642-EVAL

#### L. Mechanical Requirements

**Mechanical Size:** The dimensions of the BEU8642-EVAL are in accordance with the box outline. The edge measurements are as follows:

Length: 12.00" Width: 9.00" Height: 2.65"

Connector Types: Tyco Electronics-Amp

– 206151-1 On unit

- 206150-1 Mating Connector

### **Pinouts and Description**



External view of male connector mounted on 8642-EVAL unit



RELEASED 1/29/09

# BEU8642-EVAL

Pin #	Description	Pin #	Description	Pin #	Description	Pin #	Description
1	CELL 2+	11	TEMP ERR 1	21	LOW CELL	31	NC
2	CELL 4+	12	TEMP ERR 2	22	BIT	32	+28V RTN
3	CELL 6+	13	TEMP ERR 3	23	TS1 RTN	33	+28V RTN
4	CELL 8+	14	TEMP ERR 4	24	TS2 RTN	34	ON HI
5	CELL 1+	15	OUTPUT RTN	25	TS3 RTN	35	OFF HI
6	CELL 3+	16	TS1	26	TS4 RTN	36	OFF LO
7	CELL 5+	17	TS2	27	PS_MON	37	ON LO
8	CELL 7+	18	TS3	28	RS232 OUT		
9	CELL RTN	19	TS4	29	+28VDC		
10	PRE CONDITION	20	HIGH CELL	30	+28VDC		

#### Note:

Cell 1+ connects to the top (+) of the battery stack and CELL RTN connects to the bottom (-) of the battery stack

### **Standard Configuration**

#### **Power Requirement**

83 mA Typ at +28V<sub>DC</sub>

#### **Operating Temperature**

0°C to +70°C

#### **Storage Temperature**

-40°C to +85°C

### **Ordering Information**

Model Number BEU8642-EVAL



## BEU8642-EVAL

## Datasheet Definitions

	DEFINITION
Advanced Datasheet	CAES reserves the right to make changes to any products and services described herein at any time without notice. The product is still in the development stage and the datasheet <b>is subject to change</b> . Specifications can be <b>TBD</b> and the part package and pinout are <b>not final</b> .
Preliminary Datasheet	CAES reserves the right to make changes to any products and services described herein at any time without notice. The product is in the characterization stage and prototypes are available.
Datasheet	Product is in production and any changes to the product and services described herein will follow a formal customer notification process for form, fit or function changes.

The following United States (U.S.) Department of Commerce statement shall be applicable if these commodities, technology, or software are exported from the U.S.: These commodities, technology, or software were exported from the United States in accordance with the Export Administration Regulations. Diversion contrary to U.S. law is prohibited.

Cobham Long Island Inc. d/b/a Cobham Advanced Electronic Solutions (CAES) reserves the right to make changes to any products and services described herein at any time without notice. Consult an authorized sales representative to verify that the information in this data sheet is current before using this product. The company does not assume any responsibility or liability arising out of the application or use of any product or service described herein, except as expressly agreed to in writing; nor does the purchase, lease, or use of a product or service convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual rights of the company or of third parties.

